



LED MODULE Bridgelux diode with a 3 step MacAdams ellipse

THERMAL MANAGEMENT The fixture is designed with a special passive heat sink to keep it running well below specifications. This ensures long life in excess of 50,000 hours.

OPTICAL SYSTEM 3.25" diameter aluminized reflectors are over 89% efficient and are interchangeable with a snap on connector.

CONSTRUCTION Extruded aluminum heat sink, fabric shade 20', 3 wire cord cuttable in the field

ELECTRICAL The LED driver is mounted in a surface canopy or remote enclosure. 0-10 V dimming is standard

LISTING UL for US and Canada, Suitable for listed damp location

WARRANTY 5 Year Full Warranty

DIMMING Dimming capabilities to dim down to 1% *. 0-10V dimming

VOLTAGE 120~277V

LUMEN OUTPUT Provides 12,440 lumens, 132.5 LPW
Consult IES files for specific lumen values
(available at www.chameleonltg.com)

BUILD YOUR PRODUCT

Grayed areas are codes for creating your lighting catalog #
EXAMPLE CATALOG # AD-W-P59/P59-S-CORD-S-LED94-35-8-R64/SDE-S-P59-94/ILT-30

STYLE	SHADE FINISH	LIGHT SOURCE
<input type="checkbox"/> AD	<input type="checkbox"/> W White Acrylic <input type="checkbox"/> C Custom	<input type="checkbox"/> P59

LIGHT SOURCE	FINISH	MOUNTING	CORD COLOR	WATTAGE (WATTS)	COLOR TEMP.	CRI	BEAM SPREAD
<input type="checkbox"/> P59	<input type="checkbox"/> S Silver	<input type="checkbox"/> Cord	<input type="checkbox"/> S Silver	<input type="checkbox"/> LED94 94 watts	<input type="checkbox"/> 30 3000 <input type="checkbox"/> 35 3500 <input type="checkbox"/> 40 4000	<input type="checkbox"/> 8 80	<input type="checkbox"/> R39 39 Degree <input type="checkbox"/> R64 64 Degree

DRIVER HOUSING	FINISH	SOURCE
<input type="checkbox"/> SDE Surface Drive Enclosure  2.25" H x 12.25"	<input type="checkbox"/> S Silver	<input type="checkbox"/> P59-94

SHADE ILLUMINATION	COLOR TEMP.
<input type="checkbox"/> ILT	<input type="checkbox"/> 30 3000K <input type="checkbox"/> 35 3500K

* 25 watt, 3200lm illuminated cylinder w/
its own driver *120~277V *Dimmable 0-10V
*to be installed using separate 2 wire cord,
supplied by contractor

OPTIONAL EMERGENCY BACKUP (FIELD INSTALLED)

<input type="checkbox"/> CHA-EM-ITA	Yes
<input type="checkbox"/> (blank)	No